

Technical Specifications Mx2wire+ Media Converter







Models	Mx2wire+ set pure white (additional models in development)
Data transfer speed	up to 50 Mbps (depending on distance); see table below
Max. range	500 yds (up to 45 Mbps)
Interfaces	Front: RJ45 (Fast Ethernet, PoE), DC jack Rear: Screw terminals to attach the two-wire cable power supply connection
Certificates	EMC (EN55022, EN55024, EN61000-6-1, FCC part15B, AS/NZS3548)
Power supply (Mx2wire+ & end device)	Feed: PoE, PoE+ or 48-57 V DC Own consumption: 6 W, power output: up to 13 W

Status display	Status LED 1: Network connection, power supply Status LED 2: Active data transfer via AB wire, user connected to the opposite side
Weight	770 g (per packaging unit, set)
Operating temperature	(-22 to +122 °F)
Dimensions	3,15" x 3,15" x 1,50" (flush-mounted model) 3,15" x 3,15" x 1,77" (on-wall model)
Standard delivery	Mx2wire+ media converter set (color: pure white), mounting parts, various panel frames, manual


Technical information subject to change without notice!


Mx2wire+


Components (Shipped With Every Mx2wire+ Set)


<p>Mx2wire+ set MX-2wirePlus-Set-PW (pure white)</p>  <p>An existing Mx2wire+ set contains all components necessary to set up an Ethernet connection using a two-wire cable (telephone, coaxial, bell wire, Cat. 7). Each one is supplied with a sender/receiver unit, as well as accessories for flush-mounting or on-wall assembly and manual. The set is available in pure white at present.</p>	<p>Circuit board</p>  <ul style="list-style-type: none"> • 2x Mx2wire+ circuit board and housing 	<p>Panel frames</p>  <ul style="list-style-type: none"> • 6x white concave, convex and flat frames (two of each) 	<p>Front panels</p>  <ul style="list-style-type: none"> • 2x front panel 	<p>Surface-mounted Socket</p>  <ul style="list-style-type: none"> • 2x white surface-mounted socket 	<p>Accessories</p>  <ul style="list-style-type: none"> • 2x cavity socket • Mounting parts
---	--	--	---	---	---

Comparative Tables For The Transfer Rates Of Data And Power

Antenna or coaxial cable	Thickness	Length		
		50 yds	100 yds	500 yds
	23 AWG Inner conductor	Data: 50 Mbps Power Out: 13 W	Data: 50 Mbps Power Out: 11 W	Data: 45 Mbps Power Out: -

Telephone line/bell wire	Thickness	Length		
		50 yds	100 yds	200 yds
	23 AWG	Data: 50 Mbps Power Out: 13 W	Data: 50 Mbps Power Out: 13 W	Data: 50 Mbps Power Out: 8 W
	20 AWG	Data: 50 Mbps Power Out: 13 W	Data: 50 Mbps Power Out: 13 W	Data: 50 Mbps Power Out: 13 W

Installation cable	Thickness	Length		
		50 yds	100 yds	200 yds
	15 AWG	Data: 50 Mbps Power Out: 13 W	Data: 50 Mbps Power Out: 13 W	Data: 50 Mbps Power Out: 13 W

Network installation	Type	Length (Use of All 4 Wire Pairs: Combine 4x white and 4x colored and attach wire-end sleeves)		
		200 yds	300 yds	500 yds
	Cat-7	Data: 50 Mbps Power Out: 13 W	Data: 50 Mbps Power Out: 13 W	Data: 45 Mbps Power Out: 12 W

Mx2wire+ requires a voltage supply by a standard PoE switch (class 0 or class 4, IEEE 802.3af/at) for its own consumption as well as for supplying power to the connected PoE end device. This can either be the NPA-PoE-Set by MOBOTIX or a DC power supply unit (48-57 V, 600mA).